



MX-120M

19" MIXING AMPLIFIER

Compact and universally deployable mixing amplifier that pumps out 120 Watts. The MX-120M has integrated FM with Bluetooth and a treble/bass tone control on board. It has individual input gain control (3 channels) and is protected against short-circuit and thermal overload.



The MX-120M is suitable for a large number of purposes. It ensures a perfectly appropriate atmosphere in this shoe shop. But also the local sports centre, the Commune Council Chamber and the school ... are its playground.



output capacity 100V	120W
output capacity RMS 80	120W
frequency range	80Hz - 16kHz (+1dB, -3dB)
zones	1
direct output	70V / 100V / 4-16Ω
tone control	bass, treble
built-in music source	USB/SD - FM tuner - Bluetooth
line out	1x RCA (1000mV / 470Ω)
MIC input	1x jack 6,3mm (MIC-1) 4x euro terminal (MIC1-4 line / mic / phantom switch)
AUX input	2 RCA
priority levels	1x EMC (euro terminal) EMC>MIC1>MIC2>MIC3>MIC4/AUX1/ AUX2/MP3
power supply	240V AC
power consumption	180W
dimensions (h x w x d)	44 x 484 x 260mm - 1RS
weight	3,7kg
extra	remote control
accessories	MIC-621A / MIC-511C

