



MX-5006M

6-ZONE 19" SELECTIVE MIXING AMPLIFIER

Just choose between radio or a wireless BT-connection and in no time, you will create 6 zones that operate independently (one source at a time). They each have their own volume level and selective PA option.



Does one zone require more power than the other? That is a piece of cake for the MX-5006M. An appeal to the person responsible for the department is also easily done.



output capacity 100V	500W
output capacity RMS 80	500W
frequency range	50Hz - 16kHz
zones	6
direct output	70V / 100V / 4-16Ω
tone control	yes (per input)
built-in music source	USB/SD - FM tuner - Bluetooth
line out	yes
MIC input	4 (combo XLR/Jack) + 2 (selective paging RJ45)
AUX input	2 (RCA)
chime function	yes
priority levels	5
	EMC input (externally injected signal)
	ALARM trigger (built-in)
	TEL input / REMOTE MIC (MIC-216)
	CHIME
	MIC1 (prior to MIC2-4/LINE1-2)
power supply	240V AC / 24V DC
power consumption	360W
dimensions (h x w x d)	88 x 484 x 353mm - 2RS
weight	7,2kg
accessories	MIC-216 / MIC-511C / MIC-621A / WMS-100 / WBS-200
extra	remote controls

